



PLATFORM ADAPTATION AND BRING-UP GUIDE

DA_08477-001 | March 3, 2017

Tegra Linux Driver Package for Jetson TX2



DOCUMENT CHANGE HISTORY

DA_08477-001

Version	Date	Authors	Description of Change
v1.0	2 Mar 2017	twarren/bbasu/snath	Initial release for Jetson TX2
v1.1	14 Mar 2017	bbasu	Added Power Tree changes

TABLE OF CONTENTS

Platform Adaptation and Bring-Up Guide	4
Board Naming.....	4
Placeholders in the Porting Instructions.....	5
Pinmux Changes.....	5
Porting U-Boot.....	6
Porting the Linux Kernel.....	7
Power Tree Changes	8
Another Example.....	8
USB Lane Mapping	9
Required Device Tree Changes	10
Flashing the Build Image.....	11
Hardware Bring-Up Checklist	11
Before Power-On	11
Initial Power-On	11
Initial Software Flashing	12
Power	12
Power Optimization	12
USB 2.0 PHY	12
USB 3.0	13
HDMI.....	13
Audio.....	13
UART.....	14
SD Card (SDMMC1)	14
Sensors I2C: General	14
Sensors I2C: Touch Screen (Optional).....	14
PEX (Optional)	14
SATA (Optional)	15
Embedded Display(s) (Optional).....	15
Imager(s) (Optional)	15
Software Bring-Up Checklist	16
Preparation	16
Bring-up Hardware Validation.....	16
U-Boot Port and Boot Validation.....	16
Kernel and Peripherals, Port and Validation.....	16
System Power and Clocks	17

PLATFORM ADAPTATION AND BRING-UP GUIDE

This document is for software developers whose target is the NVIDIA® Jetson™ TX2 module. It describes how to port the NVIDIA® Tegra® Linux Driver Package and the U-Boot bootloader from NVIDIA® Jetson™ TX2 Developer Kit to other hardware platforms.

The examples described include code for the Jetson TX2 Developer Kit (P2771).

BOARD NAMING

To support your board in L4T, you must select a simple lower-case, alpha-numeric name for your board. The name can include dashes (-) or underscores (_) but cannot contain spaces. For example:

```
jetson-tx2  
p2771-000-500  
myboard
```

The name you select appears in:

- Filenames and pathnames
- U-Boot and Linux kernel source code
- User-visible device tree filenames

Additionally, this name is exposed to the user through the U-Boot command prompt and various Linux kernel `proc` files.

In this document, `<board>` represents your board name.

You must also select a similarly-constructed vendor name. The same character set rules apply, such as the following example:

```
nvidia
```

In this document, `<vendor>` represents your vendor name.

Note: Do not re-use and modify the existing NVIDIA® Jetson™ TX2 Developer Kit code without selecting and using your own board name. If you do not use your own board name it will not be obvious to Jetson TX2 users whether the modified source code supports the original Jetson TX2 Developer Kit board or your board.

PLACEHOLDERS IN THE PORTING INSTRUCTIONS

Placeholders are used throughout this document, substitute an appropriate value for each placeholder when you enter the commands.

- `<function>` is a functional module name, which may be `power-tree`, `pinmux`, `sdmmc-drv`, `keys`, `comm` (Wifi/BT), `camera`, etc.
- `<board>` is a name you have selected to represent your platform. For example, `p2771` is the name of the Jetson TX2 Developer Kit. NVIDIA `<board>` names use lower case letters.
- `<version>` is a board version number, such as `a00`. Files for NVIDIA reference boards include a version number. Files for customer platforms are not required to include a version number.
- `<vendor>` is the name of your organization, or the name of the vendor for your board.
- `<root>` is the device that holds root file system for the platform. At present, the supported value is `emmc`.

PINMUX CHANGES

If your board schematic differs from that for Jetson™ TX2 Developer Kit board, you must change the pinmux configuration applied by the software.

The `Jetson_TX2_customer_pinmux_release.xlsxm` spreadsheet is provided to:

- Show the locations and default pinmux settings
- Define the pinmux settings in the source code or device tree

The spreadsheet is available at:

<https://developer.nvidia.com/embedded/downloads>

You must customize the spreadsheet for the configuration of your board.

For information on customizing the configuration files, refer to the *Tegra Linux Driver Package Development Guide* “MB1 Platform Configuration” and “Configuring Pinmux, GPIO and PAD” topics.

PORTING U-BOOT

Perform the following actions in the U-Boot source code to add support for your board.

1. Copy `include/configs/p2771-0000.h` to `include/configs/<board>.h`.
2. Edit the set of enabled devices and features in `<board>.h` as appropriate for your board. For example, you must change the following:

```
#define CONFIG_TEGRA_BOARD_STRING      "NVIDIA p2771-0000"
```

3. Copy `arch/arm/dts/tegra186-p2771-0000-500.dts` to `arch/arm/dts/tegra186-<board>.dts`.
4. Edit the set of enabled devices and their parameters (e.g. GPIO and IRQ IDs) in `tegra186-<board>.dts` as appropriate for your board.

You may need to add, remove, or edit nodes and properties.

Note:

U-Boot and the Linux kernel do not always use the exact same device tree schema (bindings) to represent the same data. Follow examples from U-Boot rather than from the Linux kernel.

5. Add `tegra186-<board>.dtb` to `arch/arm/dts/Makefile`.
6. Copy `configs/p2771-0000-500_defconfig` to `configs/<board>_defconfig`.
7. Edit `<board>_defconfig` to refer to your board name.
8. Edit `arch/arm/mach-tegra/tegra186/Kconfig` to add target config and `Kconfig`.
9. Copy the `board/nvidia/p2771-0000/` directory to `board/<vendor>/<board>/`.
10. Edit all the files in `board/<vendor>/<board>/` to refer to your board name rather than the `p2771-0000`. The files in this directory contain many instances of the `p2771-0000` board name.
11. Edit `board/<vendor>/<board>/MAINTAINERS` to provide the correct maintainer contact information for your board.
12. Edit `board/<vendor>/<board>/<board>.c` to provide the correct PMIC programming for your board, if required.

PORTING THE LINUX KERNEL

It is assumed that you are using the CVM module provided by NVIDIA and that it has not been modified; the eMMC, PMIC, and DDR are the same with the same routing of lines. The modifications you are making are for the CVB baseboard that hosts all the peripherals. Consequently, based on the peripherals present on your baseboard, you can modify the `.dts` files by disabling/enabling the controllers and changing the supplies.

To port the kernel configuration code (the device tree) to your platform, modify one of the distributed configuration files to describe the design of your platform.

The configuration files available at:

```
<top>/hardware/nvidia/platform/t18x/  
<top>/hardware_nvidia/soc/t18x
```

The final DTB file used is:

```
tegra186-quill-p3310-1000-a00-00-base.dts
```

By reading the above file, you see which other `.dtsi` files are referenced by include statements. Common `.dtsi` files that may be modified to reflect hardware design changes include:

Types of Changes	DTSI Filename or location
Power supply changes	tegra186-quill-power-tree-p3310-1000-a00-00.dtsi
Regulator parameter changes	tegra186-quill-spmic-p3310-1000-a00-00.dtsi
Display panel and node changes	Refer to the <i>Tegra Linux Driver Package Development Guide Display Configuration and Bringup</i> topic for details.
ODM data based feature configuration	tegra186-odm-data-plugin-manager.dtsi
Tegra SOC controller state to enable/disable a controller	soc/t18x/kernel-dts/tegra186-soc/
Panels related <code>.dts</code> files	tegra/common/kernel-dts/panels/

Verify that no other `.dts` or `.dtsi` file, including these `.dts` files, overrides any changes you make.

As a best practice, create your own set of `.dts` files based on the Quill files already present. Rename your newly created files to the name of your board.

Note: Use `fdtdump` or `dtc` to generate a `.dts` from the final `.dtb` file and

check if your changes have taken effect.

The command usage is as follows:

```
dtc -I dtb -O dts tegra186-quill-p3310-1000-a00-00-base.dtb > tegra186-
quill-p3310-1000-a00-00-base.dts
fdtdump dts tegra186-quill-p3310-1000-a00-00-base.dtb > tegra186-quill-
p3310-1000-a00-00-base.dts
```

Power Tree Changes

The Jetson P2597 baseboard has a GPIO expander. Some of the pins on the GPIO expander are used as a GPIO regulator. One such usage is to enable `vbus-2-supply` which is powered using `vdd_usb2_5v` GPIO regulator. If your custom board does not have the `vdd_usb2_5v` supply, the `xhci` driver enumeration fails on the target system. To solve this situation, you must:

1. Change the supply with `battery_reg` using the `.dtsi` file located at:

```
hardware/nvidia/platform/t18x/common/kernel-dts/t18x-common-
platforms/tegra186-quill-power-tree-p3310-1000-a00-00.dtsi
```

2. Regenerate the DTB.
3. Flash with the correct DTB.

The modifications are as follows:

```
pinctrl@3520000 {
    vbus-0-supply = <&vdd_usb0_5v>;
    vbus-1-supply = <&vdd_usb1_5v>;
    vbus-2-supply = <&battery_reg>;
    vbus-3-supply = <&battery_reg>;
    vddio-hsic-supply = <&battery_reg>;
    avdd_usb-supply = <&spmic_sd3>;
    vclamp_usb-supply = <&spmic_sd2>;
    avdd_pll_erefeut-supply = <&spmic_sd2>;
};
```

Another Example

If you wish to:

- Disable `xhci` which is a USB 3.0/USB 2.0 controller, disable the following node.
- Change the lane configuration, update the following node.

```
xhci@3530000 {
    status = "disabled";
    phys = <&tegra_xusb_padctl TEGRA_PADCTL_PHY_UTMI_P(0)>,
          <&tegra_xusb_padctl TEGRA_PADCTL_PHY_UTMI_P(1)>,
          <&tegra_xusb_padctl TEGRA_PADCTL_PHY_USB3_P(1)>;
    phy-names = "utmi-0", "utmi-1", "usb3-1";
};
```

For the detailed information about .dts files, refer to the documentation at [Documentation/devicetree/bindings](#) in the NVIDIA released Linux kernel source package.

USB LANE MAPPING

USB 3.0 has 4 super-speed ports. Not all can be used in the same implementation because of lane sharing between PCIE, SATA, and XUSB. Possible combinations for USB 3.0 are as follows.

Configs	Jetson TX2 Pin Names			PEX1	PEX_RFU	PEX2	USB_SS1	PEX0	USB_SS0	SATA
	Tegra Lanes			Lane 0	Lane 1	Lane 3	Lane 2	Lane 4	See Note 1	Lane 5
	Available Outputs from Jetson TX2									
	USB 3.0	PCIe	SATA							
1	0	1x1 + 1x4	1	PCIe#2_0	PCIe#0_3	PCIe#0_2	PCIe#0_1	PCIe#0_0		SATA
2*	1	1x4	1		PCIe#0_3	PCIe#0_2	PCIe#0_1	PCIe#0_0	USB_SS#0	SATA
3	2	3x1	1	PCIe#2_0	USB_SS#1	PCIe#1_0	USB_SS#2	PCIe#0_0		SATA
4	3	2x1	1		USB_SS#1	PCIe#1_0	USB_SS#2	PCIe#0_0	USB_SS#0	SATA
5	1	2x1 + 1x2	1	PCIe#2_0	USB_SS#1	PCIe#1_0	PCIe#0_1	PCIe#0_0		SATA
6	2	1x1 + 1x2	1		USB_SS#1	PCIe#1_0	PCIe#0_1	PCIe#0_0	USB_SS#0	SATA
* Default Usage on Carrier Board				Unused	X4 PCIe Connector				USB 3 Type A	SATA

** Notes:

- PCIe Interface #2 can be brought to the PEX1 pins, or USB 3.0 Port #1 to the USB_SS0 pins on Jetson TX2 depending on the setting of a multiplexor on the module. The selection is controlled by QSPI_IO2 configured as a GPIO.
- Jetson TX2 has been designed to enable use cases listed in this table. However, released Software may not support all configurations, nor has every configuration been validated.
 - Configuration #1 & 2 represent the supported and validated Jetson TX2 Developer Kit configurations. The released software supports these configurations. The PCIe, USB 3.0, and SATA interfaces have been verified on the carrier board.
- The cell colors highlight the different PCIe and USB 3.0 Ports.
 - Three shades of green are used for PCIe interfaces #[2:0].
 - Three shades of blue are used for USB 3.0 ports #[2:0].
 - SATA is highlighted in orange.

The customer pinmux spreadsheet contains all Jetson TX2 pin names and ball names to represent which ball names are used for the super-speed connector, and the pinmux configuration of those pins.

An example configuration is available in the *Jetson TX2 OEM Product Design Guide*. Each external super-speed connector has both USB 2.0 (DP, DN) and USB 3.0 lines (TX+, RX+) linked to the connector. A possible exception is where a fixed on-board device is connected to super-speed lines and does not require USB 2.0 compatibility.

Required Device Tree Changes

The following device tree properties must change when USB configuration changes, for example, for one USB 2.0 and one USB 3.0 port used in the `xhci` controller.

Under the XHCI node:

- List all UPHY lanes required, for example:

```
phys = <PADCTL_UTMI(0)>, // for USB2.0 port0
      <PADCTL_USB3(0)>, // for USB3.0 port0
```

- Provide a naming convention to retrieve the above UPHYs from the kernel:

```
phy-names = "utmi-0", "usb3-0";
```

Under pinctrl to pinmux node:

- Create a node for each UPHY lane, for example:
 - For usb2.0, usb2-port0 { // node name could be anything
 - `nvidia,lanes = "otg-0";` // Required properties.
 - `nvidia,function = "xusb";` // Optional properties, as per padctrl documentation, function property is required for USB2.0 port and in this case, it is "xusb"
 - `nvidia,port-cap = "PORT_HOST_ONLY";` // Optional properties and could be "PORT_OTG"
 - For USB3.0, usb3-port0 {
 - `nvidia,lanes = "usb3-0";` // required property
 - `nvidia,port-cap = "PORT_OTG_CAP";` // required property for lane usb3-0.

The above allocations will work when UPHY lanes are owned by each client (`xhci/xudc/pcie..`).

As per the above example:

- XHCI must be owned by LAN0 for usb3-0.
- Lane allocation can be performed by either ODMDATA or allotted to UPHY to each client in the bmp-dtb file.
- ODM Data: Bit 24 to 28 are used to allocate lanes with Lane3, by default, is allocated to PCIE.
- ODMDATA=0x1090000; While flashing for Jetson TX2.

Lane allocations are as follows:

28	27	26	25	24
USB PHY Lane5	USB PHY Lane4	USB PHY Lane2	USB PHY Lane1	USB PHY Lane0

For the detailed information about UPHY lanes, refer to the documentation at:

```
kernel/t18x/Documentation/devicetree/bindings/pinctrl/nvidia,tegra186-padctl.txt
```

FLASHING THE BUILD IMAGE

When flashing the build image, use your specific board name. The flashing script uses the configuration present in the <board>.conf file during the flashing process.

To flash the build image

- Execute the following command.

```
$ sudo ./flash.sh <board> mmcblk0p1
```

HARDWARE BRING-UP CHECKLIST

This section provides a checklist for the platform hardware bring-up process.

Before Power-On

Make sure that the Jetson TX2 is connected to the BTB connector correctly and securely.	<input type="checkbox"/>
Verify that power supplies are not shorted to ground or to other power supplies.	<input type="checkbox"/>

Initial Power-On

Verify that VDD_IN from carrier board is in the 6 V to 19 V range.	<input type="checkbox"/>
Verify that CARRIER_WR_ON goes to HIGH when power is turned on.	<input type="checkbox"/>

Verify that system can enter force recovery.	<input type="checkbox"/>
--	--------------------------

Initial Software Flashing

Verify that system can be flashed with TegraFlash.	<input type="checkbox"/>
Verify that TegraBoot and U-boot run to completion by checking log output.	<input type="checkbox"/>
Verify that OS runs to desktop.	<input type="checkbox"/>
Verify that any UARTs intended for debugging are enabled and functional.	<input type="checkbox"/>

Power

Verify that all supplies required on at power-on are enabled appropriately.	<input type="checkbox"/>
Verify that all supplies required off at power-on are not enabled initially.	<input type="checkbox"/>
Verify that each controllable supply can be enabled and disabled, and different voltage levels can be set if applicable.	<input type="checkbox"/>
Verify that carrier board power-on sequence starts after CARRIER_PWR_ON signal is asserted.	<input type="checkbox"/>

Power Optimization

Capture CPU PWR Request entering and exiting Suspend (LP1) and Deep Sleep (LP0). Ensure that CPU PWR Request and associated power rail sequence meets Tegra Data Sheet requirements.	<input type="checkbox"/>
Verify that all rails which must be OFF in Deep Sleep (LP0) are OFF.	<input type="checkbox"/>
Verify that all rails which must be ON in Deep Sleep (LP0) are ON.	<input type="checkbox"/>
Verify that required rails are back and at correct voltage under hardware control exiting Deep Sleep (LP0).	<input type="checkbox"/>

USB 2.0 PHY

Verify that USB0 supports USB Recovery (device mode).	<input type="checkbox"/>
Verify that USB0 device mode works with intended peripheral types, if supported.	<input type="checkbox"/>
Verify USB0, USB1 and or USB2 Host mode, if implemented.	<input type="checkbox"/>
Verify USB0 Device/Host detection, if supported.	<input type="checkbox"/>
Verify that USB PHYs go to lowest power mode when not used or when the system is in low power mode.	<input type="checkbox"/>
Verify that AVDD_USB and AVDD_PLL_UTMIP are off during Deep Sleep (LP0).	<input type="checkbox"/>
Capture USB0_D+/D- signals at both ends of link (connector and test points near Tegra).	<input type="checkbox"/>
Capture USB2_D+/D- signals at both ends of link (connector and test points near Tegra).	<input type="checkbox"/>

Using USB-IF procedures, verify that signals meet requirements (correct eye height/width, etc.).	<input type="checkbox"/>
If USB signals do not meet requirements, use the <i>Tegra USB Tuning Guide</i> to adjust settings until requirements are met.	<input type="checkbox"/>

USB 3.0

Verify USB 3.0 Host mode.	<input type="checkbox"/>
Verify USB 3.0 Device mode, if enabled.	<input type="checkbox"/>
Verify that the USB 3.0 interface goes to the lowest power mode when not used or when the system is in low power mode.	<input type="checkbox"/>

HDMI

Verify that HDMI-compatible display works at 1080p.	<input type="checkbox"/>
Verify that display is detected properly (HPD).	<input type="checkbox"/>
Verify that HDMI reads and writes to the display using DDC interface.	<input type="checkbox"/>
Verify that HDMI related rails are powered off when not used or system is in Deep Sleep (LP0) or Suspend (LP1).	<input type="checkbox"/>
Capture HDMI signals at the connector (using appropriate test fixture and termination).	<input type="checkbox"/>
Verify that signal quality is acceptable (meets EYE diagram, etc.). Consult <i>Tegra HDMI Tuning Guide</i> for details.	<input type="checkbox"/>
If HDMI signals do not meet requirements, use the <i>Tegra HDMI Tuning Guide</i> to adjust settings until requirements are met.	<input type="checkbox"/>

Audio

Verify reads and writes on I2C interface used for Audio Codec.	<input type="checkbox"/>
Verify that playback works properly on speakers, headphones, and headset.	<input type="checkbox"/>
Verify that capture works properly: Sound is recorded from microphone/headset if supported.	<input type="checkbox"/>
Verify that tones, voice, etc. can be heard from speakers or headphones/headset.	<input type="checkbox"/>
Verify that Audio Codec goes to lowest power mode when not in use or system enters low power mode.	<input type="checkbox"/>
Capture signals at receiver end of link, if accessible, for each I2S I/FT used.	<input type="checkbox"/>
Verify that signal quality is acceptable. Look for excessive over/undershoot and glitches on signal edges.	<input type="checkbox"/>

UART

Verify that Tegra TX/RX/CTS/RTS connects to device RX/TX/RTS/CTS for each UART used.	<input type="checkbox"/>
Verify that signal quality is acceptable. Look for excessive over/undershoot and glitches on signal edges.	<input type="checkbox"/>

SD Card (SDMMC1)

Verify proper connectivity by setting Tegra pins to GPIOs, if necessary, to debug.	<input type="checkbox"/>
Verify that basic SD commands operate properly.	<input type="checkbox"/>
Verify reads and writes for a variety of SD Cards.	<input type="checkbox"/>
Verify that SD Card insertion detection works and wakes system, if supported.	<input type="checkbox"/>
Verify that SD Card Write Protect works, if implemented.	<input type="checkbox"/>
Verify that SD Card goes to low power mode or rails are powered off when not used or in low power system state.	<input type="checkbox"/>
Verify that signal quality is acceptable when probed at receiver end (socket or test points near BTB connector or both for bidirectional signals). Look for excessive over/undershoot and glitches on signal edges and abnormal Clock duty cycle.	<input type="checkbox"/>

Sensors I2C: General

Verify that addresses of all I2C devices appear correctly, and no unknown ghost devices appear.	<input type="checkbox"/>
Verify that signal quality is acceptable, including rise times of signals, when probed at BTB connector and devices.	<input type="checkbox"/>

Sensors I2C: Touch Screen (Optional)

Verify that Reads/Writes on I2C or SPI to Touch Screen controller are functional (reading device ID or a similar register is successful).	<input type="checkbox"/>
Verify that interrupts are generated properly.	<input type="checkbox"/>
Verify functionality of Touch Screen.	<input type="checkbox"/>
Verify that Touch Screen Controller goes to lowest power mode when not used, or system is in low power state.	<input type="checkbox"/>

PEX (Optional)

Verify proper connectivity by checking lanes.	<input type="checkbox"/>
Verify that any implemented PEX interfaces transition to the lowest power state in Deep	<input type="checkbox"/>

Sleep (LP0) and Suspend (LP1).	
Verify that signal quality is acceptable when probed at receiver end of link near Tegra and device. Look for excessive over/ undershoot and glitches on signal edges.	<input type="checkbox"/>

SATA (Optional)

Verify proper connectivity by checking diff lines.	<input type="checkbox"/>
Verify that any implemented SATA interfaces transition to the lowest power state in Deep Sleep (LP0) and Suspend (LP1).	<input type="checkbox"/>
Verify that signal quality is acceptable when probed at receiver end of link near Tegra and device. Look for excessive over/ undershoot and glitches on signal edges.	<input type="checkbox"/>

Embedded Display(s) (Optional)

Verify that I2C or other control interface is able to perform writes/reads to display.	<input type="checkbox"/>
Verify that each embedded display shows correct colors.	<input type="checkbox"/>
Verify that each embedded display's backlight is enabled when in normal display mode.	<input type="checkbox"/>
Verify that each embedded display's backlight brightness can be adjusted properly.	<input type="checkbox"/>
Verify that each embedded display's backlight is disabled when in a low power mode.	<input type="checkbox"/>
Verify that each embedded display (and any display bridge) transitions to the lowest power state in Deep Sleep (LP0) and Suspend (LP1).	<input type="checkbox"/>
Verify that power-on/off sequencing of rails associated with each display meets manufacturer's requirements.	<input type="checkbox"/>
Verify DSI, LVDS or eDP timing (see <i>Tegra DC and DSI Debugging Guide</i> for details on how and what to verify).	<input type="checkbox"/>
Probe DSI, LVDS or eDP signals near panel driver, or at connector/test points if access to driver is not possible, and verify that signal quality is acceptable. Look for excessive over/undershoot and glitches on signal edges.	<input type="checkbox"/>

Imager(s) (Optional)

Verify that I2C interface writes/reads work to all cameras.	<input type="checkbox"/>
Verify that preview displays properly for all cameras.	<input type="checkbox"/>
Verify that still capture works on all cameras.	<input type="checkbox"/>
Verify that video capture works on all cameras.	<input type="checkbox"/>
Verify that cameras and related circuitry enter lowest power mode when not used or system is in a low power mode.	<input type="checkbox"/>
Verify that power-on/off sequencing of rails associated with imager module meets manufacturer's requirements.	<input type="checkbox"/>
Probe MCLK output at recommended test points, and verify that signal quality is acceptable. Look for excessive over/undershoot and glitches on signal edges.	<input type="checkbox"/>

Look for excessive over/undershoot and glitches on signal edges.	<input type="checkbox"/>
--	--------------------------

SOFTWARE BRING-UP CHECKLIST

This section provides a checklist for the software bring-up process.

Preparation

If you replaced the SDRAM MB1 BCT with a new DDR, verify it.	<input type="checkbox"/>
If you replaced the eMMC, verify its operation.	<input type="checkbox"/>
Obtain board schematics and component data sheets.	<input type="checkbox"/>
Verify power tree and modify device tree, MB1 PMIC configuration accordingly, for the base board.	<input type="checkbox"/>
Review board pinmux and modify MB1 pinmux and PAD configuration, accordingly.	<input type="checkbox"/>

Bring-up Hardware Validation

Power and Reset Sequence, Power Rail Check	<input type="checkbox"/>
Recovery Mode	<input type="checkbox"/>
NvTest (Tegra MODS) DDR, eMMC, CPU	<input type="checkbox"/>
JTAG connection check	<input type="checkbox"/>

U-Boot Port and Boot Validation

TegraFlash	<input type="checkbox"/>
UART output	<input type="checkbox"/>
KBD connection	<input type="checkbox"/>
Board config/PMIC regulator config/Pinmux/Review device tree	<input type="checkbox"/>
Verify FS support/Config boot scripts (bootcmd)	<input type="checkbox"/>
Boot to U-boot	<input type="checkbox"/>
Boot to kernel	<input type="checkbox"/>
Boot to kernel command line or custom desktop	<input type="checkbox"/>

Kernel and Peripherals, Port and Validation

Device tree review, Pinmux, GPIO, Wake pins	<input type="checkbox"/>
PMU and regulator drivers	<input type="checkbox"/>

Display/HDMI	<input type="checkbox"/>
Audio codec	<input type="checkbox"/>
Microphone and speaker	<input type="checkbox"/>
USB	<input type="checkbox"/>
SD card	<input type="checkbox"/>
Thermal Sensor	<input type="checkbox"/>
EMC DFS table	<input type="checkbox"/>
Ethernet	<input type="checkbox"/>
SATA	<input type="checkbox"/>
PCIe	<input type="checkbox"/>

System Power and Clocks

CPU/CORE/GPU DVFS	<input type="checkbox"/>
EMC DFS table	<input type="checkbox"/>
CPU/CORE EDP	<input type="checkbox"/>
GPU EDP	<input type="checkbox"/>
System EDP (Contain Current monitor & Voltage comparator)	<input type="checkbox"/>
Power Off	<input type="checkbox"/>
LPO (optional)	<input type="checkbox"/>
CPU power down	<input type="checkbox"/>
BCT, Full-speed	<input type="checkbox"/>

Notice

ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS, AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OR CONDITION OF TITLE, MERCHANTABILITY, SATISFACTORY QUALITY, FITNESS FOR A PARTICULAR PURPOSE AND ON-INFRINGEMENT, ARE HEREBY EXCLUDED TO THE MAXIMUM EXTENT PERMITTED BY LAW.

Information furnished is believed to be accurate and reliable. However, NVIDIA Corporation assumes no responsibility for the consequences of use of such information or for any infringement of patents or other rights of third parties that may result from its use. No license is granted by implication or otherwise under any patent or patent rights of NVIDIA Corporation. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. NVIDIA Corporation products are not authorized for use as critical components in life support devices or systems without express written approval of NVIDIA Corporation.

Trademarks

NVIDIA, the NVIDIA logo, Tegra, and Jetson are trademarks or registered trademarks of NVIDIA Corporation in the United States and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

© 2017 NVIDIA Corporation. All rights reserved.